

HOW TO ORDER

See the variety of switches on the next page, and follow the example below:

MW 123 T28 - $\frac{H}{2}$ - $\frac{H}{3}$ - $\frac{0}{4}$ - $\frac{A}{5}$ - $\frac{R4}{6}$

= MW 123T28HH0AR4

LEGEND

1. Basic model number for an SP3T switch

2. Isolation (Reflective or Non-Reflective)
H - High, 60 dB L - Low, 40 dB

3. Switching Speed

	Reflective	Non-Reflective
H - High	20 ns	25 ns
L - Low	100 ns	150 ns

4. TTL Control Logic

0 - Logic "0" Low Loss	Logic "1" Isolation
1 - Logic "0" Isolation	Logic "1" Low Loss

5. Power Supply

a. Voltage

A - +5V	-12V
B - +5V	-15V
C - +12V	-12V
D - +15V	-15V

b. Current

High Speed	+100 mA (+V)	- 40 mA (-V)
Low Speed	+130 mA (+V)	- 90 mA (-V)

6. Case type